

0

VIDEO	Command head #video_%c	Parameter 1 out%d	Attribute parameter onoff=%d	Attribute parameter (Only for Parameter 1) matrix=%d
	d:Operating parameter l:Operating Lock	0:all output 1-x:specified output	0:off 1:on	input select (1-4)

1

AUDIO 1	Command head #audio_%c	Attribute parameter arc=%d	Attribute parameter dec=%d
	d:Operating parameter l:Operating Lock	0:close ARC 1:open ARC,by OUT-A 2:open ARC,by OUT-B 0:unlock 1:lock	0:close audio extraction 1:open audio extraction, follow OUT-A 0:unlock 1:lock

2

EDID	Command head #edid_%c	Parameter 1 in%d	Attribute parameter data=%d
	d:Operating parameter l:Operating Lock	0:all input 1-x:specified input	0:bypass 1:1920x1200p 2-4:1080p60 2/6/8ch 5-7:4k60 420 2/6/8ch 8-10:4k60 444 2/6/8ch 11-13:4k60 422 hdr 2/6/8ch 14:copv outA 0:unlock 1:lock

3

SYSTEM POWER	Command head #power	Attribute parameter shut=%d	Attribute parameter start=%d	Query parameter help
		0:cancel timing shut down 1-x:timing shut down/s	0:cancel timing turn on 1-x:timing On/s	Query the setting of ON/OFF

4

FACTORY RESET	Command head #factory%d
	0 or 1 : factory reset

5

	Command head	Attribute parameter	Attribute parameter	Query parameter
REGISTER	#register%d	id=%15t	psd=%15t	help
	0-5:Register user grouping	numer,letter,underline:user name	numer,letter,underline:password	Query parameter

6

	Command head	Attribute parameter	Attribute parameter	Attribute parameter	Attribute parameter	Attribute parameter
IP	#ip	ip=%d.%d.%d.%d	mask=%d.%d.%d.%d	gw=%d.%d.%d.%d	dns=%d.%d.%d.%d	dhcp=%d
		0-255:IP address	0-255:MASK address	0-255:Gateway address	0-255:DNS address	0:Off DHCP 1:On DHCP

7

QUERY COMMAND #cmd

Query
parameter

help

Query IP
Setting