

Digital Audio CAT5 Extender Box With IR Kits

Features

- ◆ Allows digital signals to be transmitted using a single Cat5e or Cat6 cable.
- ◆ Supports multichannel audio.
- ◆ Select one input from Coaxial or Toslink input ports, and send S/PDIF audio signal to both Coaxial and Toslink output ports simultaneously.
- ◆ 2 Emitter output connections.
- ◆ Convenient IR confirmation LED.
- ◆ Power receptacle with LED indicator.

Specifications

- ◆ Input: Coaxial RCA Jack & Toslink port
- ◆ Output: Coaxial RCA Jack & Toslink port
- ◆ Extender Distance: 200 Meters
- ◆ DC Input Connector: 5.5 x 2.1 x 9.5 mm
- ◆ DC Input Voltage/Polarity: 12V /Center positive
- ◆ Dimensions: 88.4L x 64.5W x 29H mm
- ◆ Weight: Transmitter 59 g ; Receiver 59 g

Infrared Component

Receiver Frequency: 30 kHz to 60 kHz

Transmit Frequency: 38 kHz and 56 kHz

Range : 40ft. @38kHz.

25ft. @56kHz

Basic Setup

